FORM HC0011-5-7


MAX 250 °C

TIME (SECONDS)

CHECKED

DATE


15. 10. 17



■ How to draw the FPC


BM22 series connector is intended to carry 3A to 4A electrical current for battery application. FPC may have less flexibility than usual, since the copper foil becomes wider and thicker to carry current of 3A.

Please design the FPC to have a flexibility to absorb the displacement* of the connector casede by fixing PCB and battery.




*Possible problems caused by connector mating in incorrect positioning. Moting the connector in incorrect positioning could lose the function of the connector.

① Insulator could be broken.




② It could apply excessive mechanical stress to single side of the contact.




Electric shock hazard

Since power contact of header side is exposed, the battery may short out if you touch the contact with finger during mating operation. To avoid this accident, mounting a header on main PWB and mounting a receptacle on battery side is recommended.







EDC-343770-51-01 BM22-4S-V(51) CL677-1002-6-51

HS PART NO.

FORM HC0011-5-8